



25 PAQUIN ROAD
WINNIPEG, MB
R2J 3V9

PHONE: (204) 988-1234
FAX: (204) 654-2881

MARCH 11, 1995

MICON INFO-PAC PROGRAMMING CROSS REFERENCE TABLE

TO DETERMINE THE PROGRAM CONFIGURATION OF THE SK350, & SK421 CONTROL BOARDS A SIX DIGIT CODE IS DISPLAYED IN THE TOP DISPLAY FOR 5 SECONDS, IMMEDIATELY AFTER A HANDLE ON/OFF. FOLLOWING ARE SOME CONFIG/ CODE COMBINATIONS.

CONFIGURATION SETTINGS (IF NOT LISTED, ASSUME DEFAULT SETTINGS)	CODE
CONFIG = DEFAULT	18E444
VOL PPU = 100	16E93d
VOL PPU = 1000	16E94C
VOL PW = 17.0MS	35CA2A
VOL PW = 26.0MS	4788 18
VOL PW = 150.0MS	EA 1676
TIMES 2 = ON	12E242
TIMES 2 = ON, VOL PPU = 100, VOL PW = 2.0MS	18E738
IN COUNT = 100 (IH)	9865E 1
IN COUNT = 100, VOL PW = 2.0MS	9769E5
IN COUNT = 100, TIMES 2 = ON	9d6EdF
IN COUNT = 100, VOL PPU = 100, VOL PW = 1.0MS	9568FA
IN COUNT = 100, VOL PPU = 100, TIMES 2 = ON, VOL PW = 1.0MS	9769F8
IN COUNT = 100, PENNY PW = 2.0MS	9865E5
IN COUNT = 4000	24dCFC
NO FLOW = ON	38C424
VOL DISP = 1.00 (D100)	1CE4C4
VOL DISP = 1.0 (DX)	1A3443
SUPPRESS = 0.009 (U.S. REQUIREMENT)	18E468
SUPPRESS = 0.009, VOL PPU = 100	16E964
SUPPRESS = 0.009, VOL PW = 17.0MS	35CA5 1
SUPPRESS = 0.009, VOL PW = 26.0MS	47883F
SUPPRESS = 0.009, VOL DISP = 1.00	1CE4E8
SUPPRESS = SGC	1CE475
SUPPRESS = 0.000	18E474
GAL CONV = ON	1FE040
CURRENCY = BATCHEN	29d636
CURRENCY = PESETAS	9F6 1AC
CURRENCY = NO DP	885585
CURRENCY = 2 DP	9d63C3

DEFAULT SETTINGS			
CONFIG = DEFAULT	VOL DISP = 1.000	NO FLOW = OFF	TRANSMIT = OFF
TEST = OFF	SUPPRESS = 0.030	VOL PPU = 10	TX DISPLAY = OFF
IN COUNT = 1000	TIMES 2 = OFF	VOL PW = 4.0MS	
CURRENCY = DOLLARS	GAL CONV = OFF	PENNY PW = 4.0MS	



25 PAQUIN ROAD
WINNIPEG, MB
R2J 3V9

PHONE: (204) 988-1234
FAX: (204) 654-2881
